

A Manual for the Plan 9 assembler

Rob Pike

rob@plan9.bell-labs.com

Machines

There is an assembler for each of the MIPS, SPARC (retired), Intel 386, AMD64, Power PC, 64-bit Power PC, ARM, ARM64, and RISC-V. The 68020 assembler, 2a (no longer distributed), is the oldest and in many ways the prototype. The assemblers are really just variations of a single program: they share many properties such as left-to-right assignment order for instruction operands and the synthesis of macro instructions such as MOV to hide the peculiarities of the load and store structure of the machines. To keep things concrete, the first part of this manual is specifically about the 68020. At the end is a description of the differences among the other assemblers.

The document, “How to Use the Plan 9 C Compiler”, by Rob Pike, is a prerequisite for this manual.

Registers

All pre-defined symbols in the assembler are upper-case. Data registers are R0 through R7; address registers are A0 through A7; floating-point registers are F0 through F7.

A pointer in A6 is used by the C compiler to point to data, enabling short addresses to be used more often. The value of A6 is constant and must be set during C program initialization to the address of the externally-defined symbol a6base.

The following hardware registers are defined in the assembler; their meaning should be obvious given a 68020 manual: CAAR, CACR, CCR, DFC, ISP, MSP, SFC, SR, USP, and VBR.

The assembler also defines several pseudo-registers that manipulate the stack: FP, SP, and TOS. FP is the frame pointer, so 0(FP) is the first argument, 4(FP) is the second, and so on. SP is the local stack pointer, where automatic variables are held (SP is a pseudo-register on the 68020); 0(SP) is the first automatic, and so on as with FP. Finally, TOS is the top-of-stack register, used for pushing parameters to procedures, saving temporary values, and so on.

The assembler and loader track these pseudo-registers so the above statements are true regardless of what has been pushed on the hardware stack, pointed to by A7. The name A7 refers to the hardware stack pointer, but beware of mixed use of A7 and the above stack-related pseudo-registers, which will cause trouble. Note, too, that the PEA instruction is observed by the loader to alter SP and thus will insert a corresponding pop before all returns. The assembler accepts a label-like name to be attached to FP and SP uses, such as p+0(FP), to help document that p is the first argument to a routine. The name goes in the symbol table but has no significance to the result of the program.

Referring to data

All external references must be made relative to some pseudo-register, either PC (the virtual program counter) or SB (the "static base" register). PC counts instructions, not bytes of data. For example, to branch to the second following instruction, that is, to skip one instruction, one may write

```
BRA    2(PC)
```

Labels are also allowed, as in

```
        BRA    return
        NOP
return:
        RTS
```

When using labels, there is no (PC) annotation.

The pseudo-register SB refers to the beginning of the address space of the program. Thus, references to global data and procedures are written as offsets to SB, as in

```
MOVL   $array(SB), TOS
```

to push the address of a global array on the stack, or

```
MOVL   array+4(SB), TOS
```

to push the second (4-byte) element of the array. Note the use of an offset; the complete list of addressing modes is given below. Similarly, subroutine calls must use SB:

```
BSR    exit(SB)
```

File-static variables have syntax

```
local<>+4(SB)
```

The <> will be filled in at load time by a unique integer.

When a program starts, it must execute

```
MOVL   $a6base(SB), A6
```

before accessing any global data. (On machines such as the MIPS and SPARC that cannot load a register in a single instruction, constants are loaded through the static base register. The loader recognizes code that initializes the static base register and treats it specially. You must be careful, however, not to load large constants on such machines when the static base register is not set up, such as early in interrupt routines.)

Expressions

Expressions are mostly what one might expect. Where an offset or a constant is expected, a primary expression with unary operators is allowed. A general C constant expression is allowed in parentheses.

Source files are preprocessed exactly as in the C compiler, so #define and #include work.

Addressing modes

The simple addressing modes are shared by all the assemblers. Here, for completeness, follows a table of all the 68020 addressing modes, since that machine has the richest set. In the table, o is an offset, which if zero may be elided, and d is a displacement, which is a constant between -128 and 127 inclusive. Many of the modes listed have the same name; scrutiny of the format will show what default is being applied. For instance, indexed mode with no address register supplied operates as though a zero-valued register were used. For "offset" read "displacement." For ".s" read one of .L, or .W followed by *1, *2, *4, or *8 to indicate the size and scaling of

the data.

data register	R0
address register	A0
floating-point register	F0
special names	CAAR, CACR, etc.
constant	\$con
floating point constant	\$fcon
external symbol	name+o(SB)
local symbol	name<>+o(SB)
automatic symbol	name+o(SP)
argument	name+o(FP)
address of external	\$name+o(SB)
address of local	\$name<>+o(SB)
indirect post-increment	(A0)+
indirect pre-decrement	-(A0)
indirect with offset	o(A0)
indexed with offset	o()(R0.s)
indexed with offset	o(A0)(R0.s)
external indexed	name+o(SB)(R0.s)
local indexed	name<>+o(SB)(R0.s)
automatic indexed	name+o(SP)(R0.s)
parameter indexed	name+o(FP)(R0.s)
offset indirect post-indexed	d(o())(R0.s)
offset indirect post-indexed	d(o(A0))(R0.s)
external indirect post-indexed	d(name+o(SB))(R0.s)
local indirect post-indexed	d(name<>+o(SB))(R0.s)
automatic indirect post-indexed	d(name+o(SP))(R0.s)
parameter indirect post-indexed	d(name+o(FP))(R0.s)
offset indirect pre-indexed	d(o()(R0.s))
offset indirect pre-indexed	d(o(A0))
offset indirect pre-indexed	d(o(A0)(R0.s))
external indirect pre-indexed	d(name+o(SB))
external indirect pre-indexed	d(name+o(SB)(R0.s))
local indirect pre-indexed	d(name<>+o(SB))
local indirect pre-indexed	d(name<>+o(SB)(R0.s))
automatic indirect pre-indexed	d(name+o(SP))
automatic indirect pre-indexed	d(name+o(SP)(R0.s))
parameter indirect pre-indexed	d(name+o(FP))
parameter indirect pre-indexed	d(name+o(FP)(R0.s))

Laying down data

Placing data in the instruction stream, say for interrupt vectors, is easy: the pseudo-instructions LONG and WORD (but not BYTE) lay down the value of their single argument, of the appropriate size, as if it were an instruction:

```
LONG    $12345
```

places the long 12345 (base 10) in the instruction stream. (On most machines, the only such operator is WORD and it lays down 32-bit quantities. The 386 has all three: LONG, WORD, and BYTE. The AMD64 adds QUAD to that for 64-bit values. The 960 has only one, LONG.)

Placing information in the data section is more painful. The pseudo-instruction DATA does the work, given two arguments: an address at which to place the item, including its size, and the value to place there. For example, to define a character array

array containing the characters abc and a terminating null:

```
DATA    array+0(SB)/1, $'a'  
DATA    array+1(SB)/1, $'b'  
DATA    array+2(SB)/1, $'c'  
GLOBL   array(SB), $4
```

or

```
DATA    array+0(SB)/4, $"abc\z"  
GLOBL   array(SB), $4
```

The /1 defines the number of bytes to define, GLOBL makes the symbol global, and the \$4 says how many bytes the symbol occupies. Uninitialized data is zeroed automatically. The character \z is equivalent to the C \0. The string in a DATA statement may contain a maximum of eight bytes; build larger strings piecewise. Two pseudo-instructions, DYNT and INIT, allow the (obsolete) Alef compilers to build dynamic type information during the load phase. The DYNT pseudo-instruction has two forms:

```
DYNT    , ALEF_SI_5+0(SB)  
DYNT    ALEF_AS+0(SB), ALEF_SI_5+0(SB)
```

In the first form, DYNT defines the symbol to be a small unique integer constant, chosen by the loader, which is some multiple of the word size. In the second form, DYNT defines the second symbol in the same way, places the address of the most recently defined text symbol in the array specified by the first symbol at the index defined by the value of the second symbol, and then adjusts the size of the array accordingly.

The INIT pseudo-instruction takes the same parameters as a DATA statement. Its symbol is used as the base of an array and the data item is installed in the array at the offset specified by the most recent DYNT pseudo-instruction. The size of the array is adjusted accordingly. The DYNT and INIT pseudo-instructions are not implemented on the 68020.

Defining a procedure

Entry points are defined by the pseudo-operation TEXT, which takes as arguments the name of the procedure (including the ubiquitous (SB)) and the number of bytes of automatic storage to pre-allocate on the stack, which will usually be zero when writing assembly language programs. On machines with a link register, such as the MIPS and SPARC, the special value -4 instructs the loader to generate no PC save and restore instructions, even if the function is not a leaf. Here is a complete procedure that returns the sum of its two arguments:

```
TEXT    sum(SB), $0  
        MOVL    arg1+0(FP), R0  
        ADDL    arg2+4(FP), R0  
        RTS
```

An optional middle argument to the TEXT pseudo-op is a bit field of options to the loader. Setting the 1 bit suspends profiling the function when profiling is enabled for the rest of the program, when in user mode. For example,

```
TEXT    sum(SB), 1, $0  
        MOVL    arg1+0(FP), R0  
        ADDL    arg2+4(FP), R0  
        RTS
```

will not be profiled; the first version above would be. Subroutines with peculiar state, such as system call routines, should not be profiled.

Setting the 2 bit allows multiple definitions of the same TEXT symbol in a

program; the loader will place only one such function in the image. It was emitted only by the Alef compilers.

Subroutines to be called from C should place their result in R0, even if it is an address. Floating point values are returned in F0. Functions that return a structure to a C program receive as their first argument the address of the location to store the result; R0 is unused in the calling protocol for such procedures. A subroutine is responsible for saving its own registers, and therefore is free to use any registers without saving them (“caller saves”). A6 and A7 are the exceptions as described above.

When in doubt

If you get confused, try using the `-S` option to `2c` and compiling a sample program. The standard output is valid input to the assembler.

Instructions

The instruction set of the assembler is not identical to that of the machine. It is chosen to match what the compiler generates, augmented slightly by specific needs of the operating system. For example, `2a` does not distinguish between the various forms of MOVE instruction: move quick, move address, etc. Instead the context does the job. For example,

```
MOVL    $1, R1
MOVL    A0, R2
MOVW    SR, R3
```

generates official MOVEQ, MOVEA, and MOVESR instructions. A number of instructions do not have the syntax necessary to specify their entire capabilities. Notable examples are the bitfield instructions, the multiply and divide instructions, etc. For a complete set of generated instruction names (in `2a` notation, not Motorola's) see the file `/sys/src/cmd/2c/2.out.h`. Despite its name, this file contains an enumeration of the instructions that appear in the intermediate files generated by the compiler, which correspond exactly to lines of assembly language.

Laying down instructions

The loader modifies the code produced by the assembler and compiler. It folds branches, copies short sequences of code to eliminate branches, and discards unreachable code. The first instruction of every function is assumed to be reachable. The pseudo-instruction NOP, which you may see in compiler output, means no instruction at all, rather than an instruction that does nothing. The loader discards all NOP's.

To generate a true NOP instruction, or any other instruction not known to the assembler, use a WORD pseudo-instruction. Such instructions on RISCs are not scheduled by the loader and must have their delay slots filled manually.

MIPS

The registers are only addressed by number: R0 through R31. R29 is the stack pointer; R30 is used as the static base pointer, the analogue of A6 on the 68020. Its value is the address of the global symbol `setR30(SB)`. The register holding returned values from subroutines is R1. When a function is called, space for the first argument is reserved at `0(FP)` but in C (not Alef) the value is passed in R1 instead.

The loader uses R28 as a temporary. The system uses R26 and R27 as interrupt-time temporaries. Therefore none of these registers should be used in user code.

The control registers are not known to the assembler. Instead they are numbered registers M0, M1, etc. Use this trick to access, say, STATUS:

```
#define STATUS 12
        MOVW   M(STATUS), R1
```

Floating point registers are called F0 through F31. By convention, F24 must be initialized to the value 0.0, F26 to 0.5, F28 to 1.0, and F30 to 2.0; this is done by the operating system.

The instructions and their syntax are different from those of the manufacturer's manual. There are no `lui` and `kin`; instead there are `MOVW` (move word), `MOVH` (move halfword), and `MOVB` (move byte) pseudo-instructions. If the operand is unsigned, the instructions are `MOVHU` and `MOVBU`. The order of operands is from left to right in dataflow order, just as on the 68020 but not as in MIPS documentation. This means that the `Bcond` instructions are reversed with respect to the book; for example, a `va BGTZ` generates a MIPS `bltz` instruction.

The assembler is for the R2000, R3000, and most of the R4000 and R6000 architectures. It understands the 64-bit instructions `MOVV`, `MOVVL`, `ADDV`, `ADDVU`, `SUBV`, `SUBVU`, `MULV`, `MULVU`, `DIVV`, `DIVVU`, `SLLV`, `SRLV`, and `SRAV`. The assembler does not have any cache, load-linked, or store-conditional instructions.

Some assembler instructions are expanded into multiple instructions by the loader. For example the loader may convert the load of a 32 bit constant into an `lui` followed by an `ori`.

Assembler instructions should be laid out as if there were no load, branch, or floating point compare delay slots; the loader will rearrange—*schedule*—the instructions to guarantee correctness and improve performance. The only exception is that the correct scheduling of instructions that use control registers varies from model to model of machine (and is often undocumented) so you should schedule such instructions by hand to guarantee correct behavior. The loader generates

```
NOR      R0, R0, R0
```

when it needs a true no-op instruction. Use exactly this instruction when scheduling code manually; the loader recognizes it and schedules the code before it and after it independently. Also, `WORD` pseudo-ops are scheduled like no-ops.

The `NOSCHED` pseudo-op disables instruction scheduling (scheduling is enabled by default); `SCHED` re-enables it. Branch folding, code copying, and dead code elimination are disabled for instructions that are not scheduled.

i960

Registers are numbered R0 through R31. Stack pointer is R29; return register is R4; static base is R28; it is initialized to the address of `setSB(SB)`. R3 must be zero; this should be done manually early in execution by

```
SUBO    R3, R3
```

R27 is the loader temporary.

There is no support for floating point.

The Intel calling convention is not supported and cannot be used; use `BAL` instead. Instructions are mostly as in the book. The major change is that `LOAD` and `STORE` are both called `MOV`. The extension character for `MOV` is as in the manual: `O` for ordinal, `W` for signed, etc.

i386

The assembler assumes 32-bit protected mode. The register names are `SP`, `AX`, `BX`, `CX`, `DX`, `BP`, `DI`, and `SI`. The stack pointer (not a pseudo-register) is `SP` and the return register is `AX`. There is no physical frame pointer but, as for the MIPS, `FP` is a

pseudo-register that acts as a frame pointer.

Opcodes names are mostly the same as those listed in the Intel manual with an L, W, or B appended to identify 32-bit, 16-bit, and 8-bit operations. The exceptions are loads, stores, and conditionals. All load and store opcodes to and from general registers, special registers (such as CR0, CR3, GDTR, IDTR, SS, CS, DS, ES, FS, and GS) or memory are written as

```
MOVx    src, dst
```

where x is L, W, or B. Thus to get AL use a MOVB instruction. If you need to access AH, you must mention it explicitly in a MOVB:

```
MOVB    AH, BX
```

There are many examples of illegal moves, for example,

```
MOVB    BP, DI
```

that the loader actually implements as pseudo-operations.

The names of conditions in all conditional instructions (J, SET) follow the conventions of the 68020 instead of those of the Intel assembler: JOS, JOC, JCS, JCC, JEQ, JNE, JLS, JHI, JMI, JPL, JPS, JPC, JLT, JGE, JLE, and JGT instead of JO, JNO, JB, JNB, JZ, JNZ, JBE, JNBE, JS, JNS, JP, JNP, JL, JNL, JLE, and JNLE.

The addressing modes have syntax like AX, (AX), (AX)(BX*4), 10(AX), and 10(AX)(BX*4). The offsets from AX can be replaced by offsets from FP or SB to access names, for example extern+5(SB)(AX*2).

Other notes: Non-relative JMP and CALL have a * added to the syntax. Only LOOP, LOOPEQ, and LOOPNE are legal loop instructions. Only REP and REPN are recognized repeaters. These are not prefixes, but rather stand-alone opcodes that precede the strings, for example

```
CLD; REP; MOVSL
```

Segment override prefixes in MOD/RM fields are not supported.

AMD64

The assembler assumes 64-bit mode unless a MODE pseudo-operation is given:

```
MODE $32
```

to change to 32-bit mode. The effect is mainly to diagnose instructions that are illegal in the given mode, but the loader will also assume 32-bit operands and addresses, and 32-bit PC values for call and return. The assembler's conventions are similar to those for the 386, above. The architecture provides extra fixed-point registers R8 to R15. All registers are 64 bit, but instructions access low-order 8, 16 and 32 bits as described in the processor handbook. For example, MOVL to AX puts a value in the low-order 32 bits and clears the top 32 bits to zero. Literal operands are limited to signed 32 bit values, which are sign-extended to 64 bits in 64 bit operations; the exception is MOVQ, which allows 64-bit literals. The external registers in Plan 9's C are allocated from R15 down.

There are many new instructions, including the MMX and XMM media instructions, and conditional move instructions. MMX registers are M0 to M7, and XMM registers are X0 to X15. As with the 386 instruction names, all new 64-bit integer instructions, and the MMX and XMM instructions uniformly use L for 'long word' (32 bits) and Q for 'quad word' (64 bits). Some instructions use O ('octword') for 128-bit values, where the processor handbook variously uses O or DQ. The assembler also consistently uses PL for 'packed long' in XMM instructions, instead of Q, DQ or PI. Either MOVL or MOVQ can be used to move values to and from control registers, even when the registers might be 64

bits. The assembler often accepts the handbook's name to ease conversion of existing code (but remember that the operand order is uniformly source then destination).

C's `long long` type is 64 bits, but passed and returned by value, not by reference. More notably, C pointer values are 64 bits, and thus `long long` and `unsigned long long` are the only integer types wide enough to hold a pointer value. The C compiler and library use the XMM floating-point instructions, not the old 387 ones, although the latter are implemented by assembler and loader. Unlike the 386, the first integer or pointer argument is passed in a register, which is BP for an integer or pointer (it can be referred to in assembly code by the pseudonym RARG). AX holds the return value from subroutines as before. Floating-point results are returned in X0, although currently the first floating-point parameter is not passed in a register. All parameters less than 8 bytes in length have 8 byte slots reserved on the stack to preserve alignment and simplify variable-length argument list access, including the first parameter when passed in a register, even though bytes 4 to 7 are not initialized.

Power PC

The Power PC follows the Plan 9 model set by the MIPS and SPARC, not the elaborate ABIs. The 32-bit instructions of the 60x and 8xx PowerPC architectures are supported; there is no support for the older POWER instructions. Registers are R0 through R31. R0 is initialized to zero; this is done by C start up code and assumed by the compiler and loader. R1 is the stack pointer. R2 is the static base register, with value the address of `setSB(SB)`. R3 is the return register and also the register holding the first argument to a C function, with space reserved at `O(FP)` as on the MIPS. R31 is the loader temporary. The external registers in Plan 9's C are allocated from R30 down.

Floating point registers are called F0 through F31. By convention, several registers are initialized to specific values; this is done by the operating system. F27 must be initialized to the value `0x4330000080000000` (used by float-to-int conversion), F28 to the value 0.0, F29 to 0.5, F30 to 1.0, and F31 to 2.0.

As on the MIPS and SPARC, the assembler accepts arbitrary literals as operands to MOVW, and also to ADD and others where 'immediate' variants exist, and the loader generates sequences of `addi`, `addis`, `oris`, etc. as required. The register indirect addressing modes use the same syntax as the SPARC, including double indexing when allowed.

The instruction names are generally derived from the Motorola ones, subject to slight transformation: the '.' marking the setting of condition codes is replaced by CC, and when the letter 'o' represents 'OE=1' it is replaced by V. Thus `add`, `addo` and `subfzeo` become `ADD`, `ADDVCC` and `SUBFZEVCC`. As well as the three-operand conditional branch instruction BC, the assembler provides pseudo-instructions for the common cases: `BEQ`, `BNE`, `BGT`, `BGE`, `BLT`, `BLE`, `BVC`, and `BVS`. The unconditional branch instruction is `BR`. Indirect branches use `(CTR)` or `(LR)` as target.

Load or store operations are replaced by MOV variants in the usual way: `MOVW` (move word), `MOVH` (move halfword with sign extension), and `MOVB` (move byte with sign extension, a pseudo-instruction), with unsigned variants `MOVHZ` and `MOVBZ`, and byte-reversing `MOVWBR` and `MOVHBR`. 'Load or store with update' versions are `MOVWU`, `MOVHU`, and `MOVBZU`. Load or store multiple is `MOVMW`. The exceptions are the string instructions, which are `LSW` and `STSW`, and the reservation instructions `lwarx` and `stwcx.`, which are `LWAR` and `STWCCC`, all with operands in the usual data-flow order. Floating-point load or store instructions are `FMOVD`, `FMOVDU`, `FMOVS`, and `FMOVSU`. The register to register move instructions `fmr` and `fmr.` are written `FMOVD` and `FMOVDCC`.

The assembler knows the commonly used special purpose registers: `CR`, `CTR`, `DEC`, `LR`, `MSR`, and `XER`. The rest, which are often architecture-dependent, are

referenced as SPR(*n*). The segment registers of the 60x series are similarly SEG(*n*), but *n* can also be a register name, as in SEG(R3). Moves between special purpose registers and general purpose ones, when allowed by the architecture, are written as MOVW, replacing mfcr, mtc r, mfmsr, mtmsr, mtspr, mfspr, mftb, and many others.

The fields of the condition register CR are referenced as CR(0) through CR(7). They are used by the MOVFL (move field) pseudo-instruction, which produces mcrf or mtcrf. For example:

```
MOVFL    CR(3), CR(0)
MOVFL    R3, CR(1)
MOVFL    R3, $7, CR
```

They are also accepted in the conditional branch instruction, for example

```
BEQ      CR(7), label
```

Fields of the FPSCR are accessed using MOVFL in a similar way:

```
MOVFL    FPSCR, F0
MOVFL    F0, FPSCR
MOVFL    F0, $7, FPSCR
MOVFL    $0, FPSCR(3)
```

producing mffs, mtfsf or mtfsfi, as appropriate.

ARM

The assembler provides access to R0 through R14 and the PC. The stack pointer is R13, the link register is R14, and the static base register is R12. R0 is the return register and also the register holding the first argument to a subroutine. The external registers in Plan 9's C are allocated from R10 down. R11 is used by the loader as a temporary register. The assembler supports the CPSR and SPSR registers. It also knows about coprocessor registers C0 through C15. Floating registers are F0 through F15, FPSR and FPCR. Some machines have 32 floating registers, but we ignore them in the interest of user executable portability, at least for now.

As with the other architectures, loads and stores are called MOV, e.g. MOVW for load word or store word, and MOVW for load or store multiple, depending on the operands.

Addressing modes are supported by suffixes to the instructions: .IA (increment after), .IB (increment before), .DA (decrement after), and .DB (decrement before). These can only be used with the MOV instructions. The move multiple instruction, MOVW, defines a range of registers using brackets, e.g. [R0-R12]. The special MOVW addressing mode bits W, U, and P are written in the same manner, for example, MOVW.DB.W. A .S suffix allows a MOVW instruction to access user R13 and R14 when in another processor mode. Shifts and rotates in addressing modes are supported by binary operators << (logical left shift), >> (logical right shift), -> (arithmetic right shift), and @> (rotate right); for example R7>>R2 or R2@>2. The assembler does not support indexing by a shifted expression; only names can be doubly indexed.

Any instruction can be followed by a suffix that makes the instruction conditional: .EQ, .NE, and so on, as in the ARM manual, with synonyms .HS (for .CS) and .LO (for .CC), for example ADD.NE. Arithmetic and logical instructions can have a .S suffix, as ARM allows, to set condition codes.

The syntax of the MCR and MRC coprocessor instructions is largely as in the manual, with the usual adjustments. The assembler directly supports only the ARM floating-point coprocessor operations used by the compiler: CMP, ADD, SUB, MUL, and DIV, all with F or D suffix selecting single or double precision. Floating-point load or

store become MOVF and MOVD. Conversion instructions are also specified by moves: MOVWD, MOVWF, MOVDW, MOVWD, MOVFD, and MOVDF.

ARM64

The assembler provides access to R0 through R31. The stack pointer is R31, the link register is R30, the frame pointer is R29, and the static base register is R28. R31 is also ZR (the zero register). It's the stack pointer when used as base register in load and store instructions and as source or destination in certain forms of ADD and SUB and 'logical' (boolean) instructions. R0 is the return register and also the register holding the first argument to a subroutine. The external registers in Plan 9's C are allocated from R27 down. R17 is used by the loader as a temporary register. The assembler supports the CPSR and SPSR registers. It also knows about system registers. Floating registers are F0 through F31, FPSR and FPCR.

As with the other architectures, loads and stores are called MOV, e.g. MOVW for load or store 32-bit word, depending on the operands.

Shifts and rotates in addressing modes are supported by binary operators << (logical left shift), >> (logical right shift), -> (arithmetic right shift), and @> (rotate right); for example R7>>R2 or R2@>2. The assembler does not support indexing by a shifted expression; only names can be doubly indexed.

Arithmetic and logical instructions can have an S suffix, as ARM allows, to set condition codes.

The syntax of the MSR and MRS system-register instructions is largely as in the manual, with the usual adjustments. The assembler directly supports only the ARM floating-point operations used by the compiler: CMP, ADD, SUB, MUL, and DIV, all with F or D suffix selecting single or double precision. Floating-point load or store become MOVF and MOVD. Conversion instructions are also specified by moves: MOVWD, MOVWF, MOVDW, MOVWD, MOVFD, and MOVDF.

RISC-V

There are assemblers for 32-bit and 64-bit RISC-V, compiled from common source and closely related. The RV32IMAFDC (a.k.a., RV32GC) instruction set (base integer plus multiply and divide, atomics, float, double and compressed) and RV64GC are supported by the assemblers, conforming as usual to Plan 9 syntax rather than the form described in the RISC-V specification. General-purpose operating systems will generally assume RV32G or RV64G.

Registers are R0 through R31, with R1 used as the link register, R2 as stack pointer, R3 as static base, R8 used for the first non-FP function argument and return value, and R4 as the loader temporary. Register external variables are assigned from R7 downward. Note that these register conventions are compatible with the compressed instruction set extension — for example, the compressed form of the JAL instruction assumes that the link register is R1. FP is a pseudo-register which denotes the address of the first argument; SP is a pseudo-register which denotes the address at the end of the auto variables. Both are offsets from R2. Floating registers are F0 through F31, and CSR(1) through CSR(3). F28 through F31 are initialised by the operating system as for the Power PC. FP arguments are always passed on the stack and FP values are returned in F0.

Three-operand logical and arithmetic instructions are written in the order

op rs2, rs1, rd

where *rs2* may be omitted if it's the same as *rd*. For all but multiply and divide instructions, *rs2* may be replaced by a constant *\$con* to obtain the immediate form of the instruction (without appending I to the opcode).

Three-operand conditional branches are written in similar order

```
Bcond  rs2, rs1, dest
```

where *rs2* may be omitted to indicate comparison with R0 (which always contains zero). For example:

```
SUB    R11, R12, R13    /* R13 = R12 - R11 */
SUB    $1, R12, R13     /* R13 = R12 - 1 */
ADD    R14, R13         /* R13 += R14 */
BLT    R11, R13, done   /* if (R13 < R11) goto done */
BNE    R11, done        /* if (R11 != 0) goto done */
```

Mnemonics for conditional branches (some of which are pseudo-ops) are as in the RISC-V specification: BEQ, BNE, BGT, BGE, BLT, BLE, BGTU, BGEU, BLTU, and BLEU. SLT and SLTU compute the result of a comparison into a register. Note that the order of comparison operands is reversed relative to what one might expect (see example above). The function call instruction JAL takes an explicit link register operand, but the RET pseudo-op assumes the link register is R1. The unconditional branch is JMP, which generates a JAL with R0 as the link register. To branch to an address in a register use JMP with indirect addressing mode, or JAL for a function call.

Data movement instructions (loads, stores, and register transfers) all use MOV and variants MOVW[U], MOVH[U] and MOV[B][U] for register-width data, [unsigned] 32-bit word, halfword and byte operands. If MOV is used with a constant source operand to load a value which doesn't fit into the 12-bit signed immediate field, the loader will generate LUI and ADD instructions as appropriate.

The SYSTEM instruction is implemented: SYS \$0 is a system call, which expects its number in R8 and arguments on the user's stack. In general, SYS \$*n* generates a SYSTEM instruction with *n* shifted left 20 bits. CSRs can be accessed simply via these MOVs:

```
MOV CSR(n), Rd
MOV Rs, CSR(n)
```

The more complex swap, set and clear instructions CSRRW, CSRRS, and CSRRC are recognised with this syntax:

```
CSRRx CSR(n), Rs, Rd
CSRRx CSR(n), $imm, Rd
```

The symbol XLEN is defined by the assembler as the size in bytes of general registers (and pointers).